LOGICS EXERCISE

TU München Institut für Informatik

Prof. Tobias Nipkow Lars Hupel

SS 2017

EXERCISE SHEET 1

26.04.2017

Submission of homework: Before tutorial on 10.05.2017. Until further notice, homework has to be submitted in groups of two students.

You have to achieve a minimum combined score of 50% on your homeworks to be granted a 0.3/0.4 grade bonus on the final exam, provided that the exam is passed.

Exercise 1.1. [Short Questions]

Let M be a set of formulas, and let F and G be formulas. Which of the following assertions hold?

- 1. If F satisfiable then $M \models F$
- 2. F is valid iff $\top \models F$
- 3. If $\models F$ then $M \models F$
- 4. If $M \models F$ then $M \cup \{G\} \models F$
- 5. $M \models F$ and $M \models \neg F$ cannot hold simultaneously
- 6. If $M \models G \rightarrow F$ and $M \models G$ then $M \models F$

Exercise 1.2. [Coincidence Lemma]

Assume that for all atomic formulas A_i in F, $\mathcal{A}(A_i) = \mathcal{A}'(A_i)$. Show that

$$\mathcal{A} \models F \text{ iff } \mathcal{A}' \models F$$

Exercise 1.3. [Semantic Proof]

Let $\models F \rightarrow G$ where F and G do not share any atoms. Show that then F is unsatisfiable or G is a tautology (or both). *Hint:* you may want to use the previous result.

Exercise 1.4. [Satisfiability Algorithms]

Check the following formulas for satisfiability using one of the algorithms seen in the lecture:

- $F_1 = (\neg A \lor \neg D \lor B) \land D \land \neg B \land E \land (\neg D \lor \neg E \lor C)$
- $F_2 = (A \to C) \land (C \to E) \land (\top \to B) \land (C \land A \to D) \land (B \to A) \land (B \to E) \land (D \land E \to \bot)$
- $F_3 = (A \to E) \land (B \to \bot) \land (C \to B) \land (\top \to A) \land (E \land B \to C) \land (C \to D)$

Page 2

Homework 1.1. [CNF and DNF] (6 points) Use the rewriting-based procedure from the lecture to convert the following formulas F and G first to NNF, and then to CNF and DNF. Document each rewriting step.

$$F = \neg \neg (\neg A_1 \land \neg \neg (A_2 \lor A_3)) \qquad \qquad G = (A_1 \lor A_2 \lor A_3) \land (\neg A_1 \lor \neg A_2)$$

Homework 1.2. [Basic equivalences] (8 points) Let F and G be formulas. Are the following statements equivalent? Proof or counterexample!

- 1. $\models F \leftrightarrow G$
- 2. $F \equiv G$

How about these two statements?

- 1. F is valid
- 2. $F \equiv \top$

Homework 1.3. [Efficient CNF satisfiability check] (6 points) In general, solving satisfiability for CNF formula is a hard problem. Consider the special case where clauses may only contain up to two literals. Give an efficient algorithm to check satisfiability.